

FLAT PAR CAN

DMX CONTROL TABLE



2-CHANNEL MODE		
CHANNEL	VALUE	FUNCTION
CH1	000 - 255	Master dimmer (0-100%)
CH2	000 - 255	Colour macro
	000 - 036	Red
	037 - 073	Green
	074 - 110	Blue
	111 - 147	Yellow
	148 - 184	Magenta
	185 - 221	Cyan
	222 - 255	White

3-CHANNEL 1 MODE		
CHANNEL	VALUE	FUNCTION
CH1	000 - 255	Master dimmer (0-100%)
CH2	000 - 255	Stroboscope (rate 0 - 100%)
CH3	000 - 080	Colour macro
	000 - 004	Blackout
	005 - 015	Red
	016 - 026	Green
	027 - 037	Blue
	038 - 048	Yellow
	049 - 059	Magenta
	060 - 070	Cyan
	071 - 080	White
	081 - 150	Colour change (rate)
	151 - 220	Colour blending (rate)
	221 - 255	Music control (microphone sensitivity)

3-CHANNEL 2 MODE		
CHANNEL	VALUE	FUNCTION
CH1	000 - 255	Red (0 - 100%)
CH2	000 - 255	Green (0 - 100%)
CH3	000 - 255	Blue (0 - 100%)

6-CHANNEL MODE		
CHANNEL	VALUE	FUNCTION
CH1	000 - 255	Master dimmer (0-100%)
CH2	000 - 255	Stroboscope (rate 0 - 100%)
CH3	000 - 225	Red (0 - 100%)
CH4	000 - 225	Green (0 - 100%)
CH5	000 - 225	Blue (0 - 100%)
CH6	000 - 080	Colour macro
	000 - 004	Blackout / colour mix CH3 - CH5
	005 - 015	Red
	016 - 026	Green
	027 - 037	Blue
	038 - 048	Yellow
	049 - 059	Magenta
	060 - 070	Cyan
	071 - 080	White
	081 - 150	Colour change (rate)
	151 - 220	Colour blending (rate)
	221 - 255	Music control (microphone sensitivity)